



# IECEX Certificate of Conformity

## INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification Scheme for Explosive Atmospheres

for rules and details of the IECEx Scheme visit [www.iecex.com](http://www.iecex.com)

Certificate No.:  issue No.:

Status:

Date of Issue: **2010-08-12** Page 1 of 3

Applicant: **The Wolf Safety Lamp Co. Limited**  
Saxon Road Works  
Sheffield S8 0YA  
United Kingdom

Electrical Apparatus: **Wolf Fluorescent Leadlamp LL-500**  
Optional accessory:


Type of Protection: **Increased Safety Encapsulation and Dust**

Marking: **Ex emb II T\* (-\*\*°C to +\*\*°C)**  
**Ex embd IIC T\* (-\*\*°C to +\*\*°C)**  
**Ex tD A21 IP 66/IP 67/IP 68 T\*\*°C**

Approved for issue on behalf of the IECEx Certification Body: **C Ellaby**

Position: **Certification Officer**

Signature:  
(for printed version)



Date: 2010-08-12

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting the [Official IECEx Website](http://www.iecex.com).

Certificate issued by:

**SIRA Certification Service**  
Rake Lane  
Eccleston  
Chester  
CH4 9JN  
United Kingdom



**sira**  
CERTIFICATION



# IECEx Certificate of Conformity

Certificate No.: IECEx SIR 10.0121

Date of Issue: 2010-08-12

Issue No.: 0

Page 2 of 3

Manufacturer: **The Wolf Safety Lamp Co. Limited**  
Saxon Road Works  
Sheffield S8 0YA  
United Kingdom

Manufacturing location(s):

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended.

#### STANDARDS:

The electrical apparatus and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards:

<b>IEC 60079-0 : 2007-10</b> Edition: 5	Explosive atmospheres - Part 0: Equipment - General requirements
<b>IEC 60079-18 : 2009</b> Edition: 3	Explosive atmospheres Part 18: Equipment protection by encapsulation "m"
<b>IEC 60079-7 : 2006-07</b> Edition: 4	Explosive atmospheres - Part 7: Equipment protection by increased safety "e"
<b>IEC 61241-1 : 2004</b> Edition: 1	Electrical apparatus for use in the presence of combustible dust - Part 1: Protection by enclosures "tD"

*This Certificate does not indicate compliance with electrical safety and performance requirements other than those expressly included in the Standards listed above.*

#### TEST & ASSESSMENT REPORTS:

*A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in*

Test Report:

[GB/SIR/ExTR10.0197/00](#)

Quality Assessment Report:

[GB/BAS/QAR06.0017/02](#)



# IECEx Certificate of Conformity

Certificate No.: IECEx SIR 10.0121

Date of Issue: 2010-08-12

Issue No.: 0

Page 3 of 3

## Schedule

### EQUIPMENT:

*Equipment and systems covered by this certificate are as follows:*

These Fluorescent Luminaires are suitable for portable lighting or for use in fixed installations, they are available as either a standard version (LL-500) or an emergency version incorporating an integral battery (LL-500E). The luminaires comprise a clear, circular, polycarbonate lamp envelope with two aluminium end caps. The lamp envelope will have a clear anti static coating to safely dissipate any static electricity. The end caps are secured to the tube via the internal gear tray/reflector, which is fabricated from steel or aluminium, two M6 screws and dowty washers are used to secure each end cap. A silicone gasket is fitted within a groove on each end cap, thus maintaining the IP66/67/68 (3 m for 30 minutes) ratings; note that when sockets are fitted, only IP66 is applicable. Refer to the annexe for full description and Information regarding variants.

### CONDITIONS OF CERTIFICATION: NO

**Annexe to:** IECEx SIR 10.0121  
**Applicant:** Wolf Safety Lamp Co. Limited  
**Apparatus:** Wolf Fluorescent Leadlamp LL-500



**2xCFL Variants** – These are suitable for use with 2 x 18, 36 or 55 W compact fluorescent lamps with 2G11 base, the gear tray/reflector contains one encapsulated ballast assembly complete with associated terminal blocks on one side and lamp supports on the other, this distributes light through 180°.

**4xCFL Variants** - These are suitable for use with 4 x 18, 36 or 55 W compact fluorescent lamps with 2G11 base, each side of the gear tray/reflector contains one encapsulated ballast assembly complete with associated terminal blocks and lamp supports, this distributes light through 360°.

**2xT8 Variants** – These are suitable for use with 2 x 18, 36 or 58 W T8 fluorescent lamps, either bi pin (G13 cap) or single pin (Fa6 cap), the gear tray/reflector contains one encapsulated ballast assembly complete with associated terminal blocks on one side and bi pin or single pin lampholders on the other side, this distributes light through 180°. On emergency versions, an encapsulated inverter, fuse and Ex e battery are also present alongside the ballast.

The ballast incorporates circuit design with lamp end of life detection, which complies with the requirements of IEC 60079-7 Edition 4, Annex H. Cable entry holes for suitably ATEX or IECEx certified cable glands are provided in the end caps to facilitate through wiring of the luminaires. The supply terminal block is either a Wago 262 series terminal block, Wago 264 series terminal block, a Weidmüller Type BK4 terminal block or a Weidmüller Type MK6 terminal block, certified under IECEx PTB 04.0004U, IECEx PTB 04.0003U, IECEx SIR 05.0035U and IECEx SIR 05.0037U respectively; all terminal blocks are coded Ex e II.

The standard and emergency luminaires are designed for use with an electrical supply of either 110 V to 254 V a.c. 50/60 Hz, 110 V to 130 V a.c. 50/60 Hz or 220 to 254 V 50/60 Hz a.c. 50/60 Hz. The standard luminaire is also suitable for use with 24 or 42 Volts d.c.

The Wolf Fluorescent Leadlamp LL-500 is supplied with an alternative polyurethane end cap, which is longer and is ridged thereby minimising the risk of static electric charge when cleaning. Luminaires can be supplied with sockets fitted to the end caps with bolts, nuts and sealing washers and/or various lengths of cable with plugs fitted. The following optional certified plugs and sockets may be fitted:

Manufacturer	Type Ref.	Coded	Certificate Number
Cooper Crouse-Hinds GmbH	Type GHG 51. ....R....	Ex ed [ia] IIC T6 or T5	IECEX BKI 04.0002
Cooper Crouse-Hinds GmbH	Type GHG 57. ....R....	Ex de IIC T6 Ex tD A21 IP66 T52°C	IECEX BKI 06.0005X
R. Stahl	Type 8591/...-..-....	Ex de IIC T6 Ex ia/ib IIC T6 Ex tD A21 IP66 T52°C	IECEX BKI 07.0001X
ATX	Type PCX	Ex ed IIC T6 or T5 Ex tD A21 IP66 T68°C	IECEX LCI 04.0014
R. Stahl	Type 8570/...-..-....	Ex de IIC T6 Ex de [ia] IIC T6 Ex tD A21 IP66 80°C	IECEX PTB 05.0023

**Annexe to:** IECEx SIR 10.0121  
**Applicant:** Wolf Safety Lamp Co. Limited  
**Apparatus:** Wolf Fluorescent Leadlamp LL-500



### Options

- i. The Portable versions of the luminaires may be transported whilst energised.
  - 4 or 2 x 18 W Compact Fluorescent Lamps
  - 4 or 2 x 36 W Compact Fluorescent Lamps
  - 4 or 2 x 55 W Compact Fluorescent Lamps
- ii. Fixed installation luminaires, lamps ratings:
  - 4 or 2 x 18 W Compact Fluorescent Lamps
  - 4 or 2 x 36 W Compact Fluorescent Lamps
  - 4 or 2 x 55 W Compact Fluorescent Lamps
  - 2 x 18 W T8 Lamps Standard & Emergency Units
  - 2 x 36 W T8 Lamps Standard & Emergency Units
  - 2 x 58 W T8 Lamps Standard & Emergency Units
- iii. The LL-500 T8 lamp variants may be used as an emergency luminaires when fitted with a battery pack.
- iv. The LL-500 luminaires may be mounted in any attitude and are suitable for use with Unistrut or equivalent accessories, magnets may also be used to mount the luminaire. Alternatively, when used as a portable luminaire, a carrying strap can be fitted.
- v. The LL-500 luminaires are suitable for use with either T8 bi-pin or single pin lamps or compact fluorescent lamps.
- vi. The LL-500 luminaire may be fitted with certified plugs and sockets to the end caps.

### Full list of product markings applicable to particular models (including those introduced by variations)

#### **4 x 55 W, 36 W & 18 W CFL Standard Units:**

Ex emb II T3 (Ta = -20°C to +35°C)  
Ex embd IIC T3 (Ta = -20°C to +35°C), with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

#### **2 x 55 W, 36 W and 18 W CFL Standard Units:**

Ex emb II T3 (-20°C to +44°C)  
Ex embd IIC T3 (-20°C to +44°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

#### **2 x 58 W, 2 x 36 W & 2 x 18 W T8 Standard Units:**

Ex emb II T4 (Ta = -20°C to +53°C)  
Ex embd IIC T4 (Ta = -20°C to +53°C), with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

#### **2 x 58 W, 2 x 36 W & 2 x 18 W T8 Emergency Units:**

Ex emb II T4 (Ta = -15°C to +53°C)  
Ex embd IIC T4 (Ta = -15°C to +53°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**Annexe to:** IECEx SIR 10.0121  
**Applicant:** Wolf Safety Lamp Co. Limited  
**Apparatus:** Wolf Fluorescent Leadlamp LL-500



**2 x 36 W and 2 x 18 W CFL Standard Units fitted with Voltage Booster:**

Ex emb II T3 (-20°C to +44°C)  
Ex embd IIC T3 (-20°C to +44°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**2 x 36 W and 2 x 18 W T8 Standard Units fitted with Voltage Booster:**

Ex emb II T3 (-20°C to +44°C)  
Ex embd IIC T3 (-20°C to +44°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**4 x 36 W and 4 x 18 W CFL Units fitted with Voltage Booster:**

Ex emb II T3 (-20°C to +35°C)  
Ex embd IIC T3 (-20°C to +35°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**2 x 55 W, 36 W & 18 W CFL 360° Units:**

Ex emb II T3 (-20°C to +44°C)  
Ex embd IIC T3 (-20°C to +44°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**2 x 36 W and 2 x 18 W CFL 360° Units fitted with Voltage Booster:**

Ex emb II T3 (-20°C to +44°C)  
Ex embd IIC T3 (-20°C to +44°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T100°C

**2 x 36 W and 2 x 18 W Emergency CFL Units:**

Ex emb II T3 (-15°C to +53°C)  
Ex embd IIC T3 (-15°C to +53°C) – with plugs & sockets  
Ex tD A21 IP 66/IP 67/IP 68 (3 m for 30 minutes) T102°C

The Manufacturer shall comply with the following condition of manufacture:

1. The encapsulated parts of the apparatus shall be subjected to a visual inspection. No visible damage of the compound shall be evident, such as cracks, exposure of the encapsulated parts, flaking, impermissible shrinkage, discoloration, swelling decomposition or softening, as required by IEC 60079-18:2004 Clause 7.1.
2. An electric strength test of  $2U + 1000$  V (where U is the supply voltage) with a minimum of 1500 V ac, shall be applied between circuit and casing for at least 1 minute as required by EN 60079-7:2003 Clause 6.1. No breakdown shall occur.